



**CONTROL ANY**

Control. Anything. Anywhere.

SMART  
BE  K  
By CONTROL ANY

Control. Everything. Remotely.

## Dimensions & Weight

3.11 x 3.11 x 2.00 in  
(79mm x 79mm x 51mm)

0.5lbs / 225g

## Core

Low Power high performance CPU from TI.

Can control large variety of IR appliance

## Sensor

Temperature & Humidity Sensor

ALS sensor and Proximity sensor

## Materials & Color

ABS Body, Brushed Aluminium,  
Fiber Glass & Optics

Black  White  Blue

## Wireless Connectivity

BLE 4.2 reliable stack and device  
from Nordic Semiconductor

Zwave 5 series with Zwave+ features

Zigbee HA 1.2 stack & device from TI

IR Transceiver



## Features

- Multiple High-power IR LED for 360° control
- IR receiver that can capture signals for Remote Learning
- IR Command Storage Capability for Smart Control.
- Recipe and Schedule
- Voice Assist
- RGB glowing Indication
- OTA updates for new features and functionality
- Multiple simultaneous connection

## Works With



## Connectivity



SONOS



amazon echo

NUIMO



## Application



## In the Box

BEAK

Wall Mount Dock

Micro USB Charging Cable

4 AAA Rechargeable Battery

User Manual

